





Input impedance $970 \pm 50\Omega (13 \text{ kHz})$ or 2150 \pm 50 Ω (standard 0 µm) Phase (13 kHz): 71 ± 2°. Input resistance: $100 \pm 5Ω$. Output impedance at 13 kHz: 1000 ± 2Ω. Phase (13 kHz): 0,2° Dummy probe (halfbridge), sensivity 73,75 mV/V/m. Suitable for instruments with following features: Frequency: 13 ± 0,65 kHz, Voltage: 3 ± 0,015 Veff (2 symétrical voltages of 1,5 Veff) Input and output impedance: \leq 0,2 Ω et 2000 Ω , respectively



-10°C to 70°C



10°C to 35°C



Calibration: 40 % to 60 %. Operating: 20 % to 80 %. Storage: 5 % to 95 %. Without condensation.



IP40 (IEC 60529)



Inspection report



Ø 18 mm, length 118 mm



≈ 45 g



 $20 \pm 0,5$ °C, stabilisation time = 8 h



± 3 ppm/°C. Ageing: ± 30 ppm/a

Calibration Standards - Dummy Probes

Calibration standards – also known as "dummy probes" – are resistance dividers. Each calibration standard simulates a given length dimension with high accuracy. Each calibration standard has 2 values (positive and negative). The values indicated below are the nominal values.

These products are calibrated and supplied with an inspection report that shows the values (actual values) measured during calibration and the related measuring uncertainty.

The calibration standards are connected to the instrument in place of regular probes. For the calibration and all required setting operations of the instrument, certain criteria and conditions need to be respected. Consult the user manual or get in touch with our specialists for further information.



Set of 3 calibration standards (S41077249)

No		Value of the calibration standard (microns)
S41078077	Dummy probe	± 0
S41078079	Dummy probe	± 3
S41078228	Dummy probe	± 100
S41078230	Dummy probe	± 190
S41078087	Dummy probe	± 300
S41078332	Dummy probe	± 500
S41078751	Dummy probe	± 1000
S41078752	Dummy probe	± 1900
S41077249	Set of 3 dummy probes	± 0 / ± 100 / ± 1000
S41078654	Set of 2 dummy probes	± 190 / ± 1900

